

Built-in 2 x 90 watts (PEAK) amplifier
HDMI 2 in 1 out
1 x Minijack input
Bluetooth input (re-nameable and pin can be set)
Remote control included
RS-232
ARC HDMI Input (allows display to control volume)



Need to punch a hole in the back wall? The SB-1900P soundbar outputs truly impressive sound! The chassis has a matt black finish that enhances any audio-visual installation in meeting rooms, boardrooms, and conference rooms.

Rename Bluetooth

Set any Bluetooth name and Pin. Use PC software to load an image file onto a USB stick. Insert into the soundbar and boot up.

Multiple HDMI

Two HDMI inputs and an HDMI output make connecting to other devices easy.

ARC HDMI

If a display is connected to the ARC input on the soundbar, the display remote control will control the soundbar volume.

Analogue Input

A stereo line-level Minijack input handles normal analogue sources.

RS-232 Control

For professional integration it features RS-232 control via the USB port.

Auto Standby

Choose to use the standard auto standby setting to conserve power, or hold down VOL+ to disable auto-standby.

Hanging Brackets

A set of brackets are included which hang the soundbar under the flat panel. The speaker also comes with rubber feet if you need to place on a shelf, and wall-hanging lugs.

Power Cycling

If mains power is turned off and on, the SB-1900P will automatically come back on resuming the previous settings.

Remote Control

A remote control is included.

SPECIFICATIONS

PRODUCT DIMENSIONS

800 x 90 x 62 mm (width x depth x height)

PACKAGED DIMENSIONS

1055 x 155 x 105 mm

PRODUCT WEIGHT

2.1 kg

PACKAGED WEIGHT

3.6 kg

CONSTRUCTION MATERIAL

ABS Plastic

COLOUR

Black

AMPLIFIER OUTPUT

2 x 90 watts (PEAK) / 2 x 50w watts (RMS)

DRIVERS

4

DRIVER IMPEDANCE

4 Ohms

INPUT 1

Aux in (3.5mm) Input Sensitivity: 700mV

INPUT 2

HDMI(2 in 1 out)

TOTAL HARMONIC DISTORTION

1% (1kHz, 1W)

USB-A

for renaming Bluetooth and RS-232 control

SPEAKER IMPEDANCE

8 ohms

SENSITIVITY

91 dB (1w/1m)

FREQUENCY RESPONSE

(-3dB) 70Hz-20kHz

POWER CONSUMPTION

30w (<0.5W standby)

BLUETOOTH

V4.2

MAXIMUM POWER TRANSMITTED

<5 dBm

FREQUENCY BANDS

2402 - 2480 MHz

POWER INPUT

DC 20V/3A

REMOTE CONTROL

Distance: 6 m Angle: 30° Battery Type: CR 2025

ACCESSORIES INCLUDED

1 x Remote Control 2 x L shaped universal mounting strips – to hang soundbar beneath flat panel 1 x USB-A to 9-pin serial adaptor cable, Black 4 x 1.5 m Figure 8 power cable (right-angle plug: UK/EU/US, normal plug: AU), Black

POWER SUPPLY

External 100-240v 50/60Hz AC Power Supply – 21 volt / 3 amp. DC tail length: 1.2 m. Transformer dimensions: 128.9 x 51.3 x 34.8 mm, Pin dimensions: Length: 10mm, diameter 6.5mm

WARRANTY

Lifetime return-to-base

COMPLIANCE

RoHS, WEEE, CE/EMC, FCC, IEC, RCM-POC, RCM-SDOC, REACH, UKCA

SPARE REMOTE

SB-1900P RC [EU SAP: 4873590/ US SAP: 13445517]