



# Pair 60w Active Loudspeakers

SP-1800PBT EU SAP: 4313061 US SAP: 12928308

[vav.link/sp-1800pbt](http://vav.link/sp-1800pbt)

Integrated 2 x 30 watt (RMS) analogue amplifier  
Two inputs, IR remote included  
RS-232 Control  
Bluetooth input

Vision's premium powered bookshelf speakers are purpose-built for any audio-visual presentation environments such as classrooms and meeting rooms, or bars and restaurants. They are simple to install and sound great! Perfect for meeting spaces.



## Serial Control

RS-232 control means the SP-1800P can be controlled by a control system such as Crestron or AMX, or by Vision's own Techconnect Control.

## Auto Standby

SP-1800P feature auto standby which saves power. This feature can be disabled via the remote control or a control system.

## Remote Control

A full range of options are presented on the IR remote control, including bass and treble adjustment.

## Bass Reflex

A bass reflex port allows greater excursion of the woofer, allowing the woofer to produce lower frequencies, and the phase-delayed movement of air from behind the woofer to the front reinforces the bass even more.

## 5.25" Woofer

They are 240mm tall and use a 5.25 inch woofer – the most popular size for classroom, meeting room, and boardroom applications.

## Horizontal C bracket

The adjustable brackets allow the installer to easily angle up 30° or down 30°. Or leave the brackets off and use as shelf speakers.

## Rugged Grille

Attractive and robust, the thick metal grille protects the drivers from physical interference.

## Big Sound

These loudspeakers use three drivers; a woofer, a squawker, and a tweeter. Asking a driver to produce a wide range of frequencies is always a compromise, so dividing the sonic range into three means each driver has a narrower range of frequencies to produce, resulting in less distortion and clearer sound.

## Memory


When power is connected the SP-1800P automatically comes on and remembers the previous volume setting. Restoring power brings the loudspeakers back to life automatically.

## Bluetooth

Connect from your phone or laptop wirelessly. Speakers can auto-switch from line-level input when Bluetooth is paired if user chooses.

## Summed Inputs

The two inputs are summed to avoid the need to switch.



**VISION**

## MANUAL

Manual en v2

**EN PDF 2.40 MB**

[files.visionaudiovisual.com/products/SP-1800P/manuals/SP-1800PBT\\_manual\\_en\\_v2.pdf](files.visionaudiovisual.com/products/SP-1800P/manuals/SP-1800PBT_manual_en_v2.pdf)

## CAD

CAD

**ZIP 276.80 KB**

<files.visionaudiovisual.com/products/SP-1800P/cad/SP-1800P.zip>

CAD

**VND.DWG 329.01 KB**

<files.visionaudiovisual.com/products/SP-1800P/cad/SP-1800P.dwg>

## SOFTWARE

InstallBlueSuite 2 6 4 1046

**X-DOSEXEC 30.42 MB**

[files.visionaudiovisual.com/products/SP-1800P/software/InstallBlueSuite\\_2\\_6\\_4\\_1046.exe](files.visionaudiovisual.com/products/SP-1800P/software/InstallBlueSuite_2_6_4_1046.exe)

InstallBlueSuite 2 6 4 1046

**ZIP 30.37 MB**

[files.visionaudiovisual.com/products/SP-1800PBT/software/InstallBlueSuite\\_2\\_6\\_4\\_1046.zip](files.visionaudiovisual.com/products/SP-1800PBT/software/InstallBlueSuite_2_6_4_1046.zip)

## IMAGE

Product Images

**ZIP 8.05 MB**

<files.visionaudiovisual.com/products/SP-1800P/images/SP-1800P.zip>

Product Images

**PNG 2.32 MB**

<files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800PBT.png>

Serial rear

**PNG 1.14 MB**

[files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P\\_serial\\_rear.png](files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P_serial_rear.png)

Serial rear angle

**PNG 948.39 KB**

[files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P\\_serial\\_rear\\_angle.png](files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P_serial_rear_angle.png)

Front

**PNG 2.44 MB**

[files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P\\_front.png](files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P_front.png)

Front angle

**PNG 1.37 MB**

[files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P\\_front\\_angle.png](files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P_front_angle.png)

Dims

**PNG 19.28 KB**

[files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P\\_dims.png](files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P_dims.png)

Frequency response

**JPEG 318.33 KB**

[files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P\\_frequency\\_response.jpg](files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P_frequency_response.jpg)

Front elevation dims

**PNG 9.74 KB**

[files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P\\_front\\_elevation\\_dims.png](files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P_front_elevation_dims.png)

Remote 1

**PNG 67.95 KB**

[files.visionaudiovisual.com/products/SP-1800PBT/images/CS\\_1800P\\_remote\\_1.png](files.visionaudiovisual.com/products/SP-1800PBT/images/CS_1800P_remote_1.png)

Menu

**PNG 0.99 MB**

[files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P\\_menu.png](files.visionaudiovisual.com/products/SP-1800PBT/images/SP-1800P_menu.png)

## SPECIFICATIONS

### PRODUCT DIMENSIONS

244 x 180 x 174 mm / 9.61" x 7.1" x 6.85" (tall x wide x deep for each speaker)

### PACKAGED DIMENSIONS

465 x 205 x 270 mm / 18.3" x 8.1" x 10.63"

### PRODUCT WEIGHT

4.78 kg / 10.54 lbs (per pair)

### PACKAGED WEIGHT

5.25 kg / 11.57 lbs (per pair)

### CONSTRUCTION MATERIAL

ABS

### COLOUR

White

### AMPLIFIER OUTPUT

2 x 30 watts (RMS)

### WOOFER

5.25"

### TWEETER

0.5" + Piezo 1"

### INPUT 1

Minijack (3.5mm)

### INPUT 2

2-Phono (RCA)

### SPEAKER OUTPUT

Removable Phoenix type

### SPEAKER INPUT (ON SLAVE)

Bare-wire screw type

### OUTPUT IMPEDANCE

4 ohms

### SENSITIVITY

85 dB (1w/1m)

### FREQUENCY RESPONSE

50Hz-20kHz

### POWER CONSUMPTION

≤ 100 w

### POWER SUPPLY

100-240v 50/60Hz AC External Power Supply – 16 volt / 5.4 amp

### BLUETOOTH VERSION

4.0

### LAPTOP-STYLE TRANSFORMER

#### INCLUDES 4 X 0.5M (1.6 FT) FIGURE-8 POWER CABLES

UK/EU/US/AU

### DC TAIL LENGTH

1.5 m (4.9 ft)

### TRANSFORMER DIMENSIONS

149 x 59 x 35 mm / 5.9" x 2.3" x 1.4"

### ACCESSORIES INCLUDED

2 x Wall brackets 1 x Euro Figure-8 Power cable 0.5 m (1.6') long 1 x UK Figure-8 Power cable 0.5 m (1.6') long 1 x AU Figure-8 Power cable 0.5 m (1.6') long 1 x US Figure-8 Power cable 0.5 m (1.6') long 1 x Speaker Cable 5 m (16.4') long 1 x Remote Control (Battery included: CR2025 3V Li-Mn) 1 x Male to Male 9-Pin Serial adaptor

### WARRANTY

Lifetime return-to-base

### COMPLIANCE

RoHS, CE/EMC, FCC, RCM, RCM/TV, RCM-SDOC, REACH

### ORDER PART CODE

SP-1800PBT [EU SAP: 4313061 / US SAP: 12928308]

### SPARE REMOTE CONTROL

SP-1800P RC [EU SAP: 3940954 / US SAP: 12928050]

### SPARE POWER SUPPLY UNIT (PSU)

TC2 P16V5.4A [US SAP: 3824152/ US SAP: 13445525]

# VISION